

# MX-SERIES

STEREO MIXER WITH EFFECT & USB

# NTS



## TECHNICAL SPECIFICATION

MX-600 : Stereo Mixer 6 Mono Input  
MX-800 : Stereo Mixer 8 Mono Input  
MX-1200 : Stereo Mixer 12 Mono Input  
MX-1600 : Stereo Mixer 16 Mono Input

- 3 band EQ on all input
- 1 Aux send for external effects and monitoring
- Peak LED on all input
- PFL switch on all input
- Built in delay effect
- USB interface for MP3 input and playback
- +48V phantom power supply

## MAIN SPECIFICATION :

Channel ..... 6 mono input [MX-600]  
..... 8 mono input [MX-800]  
..... 12 mono input [MX-1200]  
..... 16 mono input [MX-1600]  
Frequency Response ..... 20Hz - 20KHz  
T.H.D. ....< 0.1% (1KHz full power)  
Signal to Noise Ratio ..... -80dB  
Input Sensitivity : Mic Input ..... -60dB  
: Stereo Input ..... -40dB  
: EFX Send ..... -20dB  
: EFX Return ..... -20dB  
Output ..... 4V max  
EQ : High ..... +/-15dB, 10KHz  
: Mid ..... +/-15dB, 250Hz - 6KHz  
: Low ..... +/-15dB, 60Hz  
Power Requirement ..... AC 220V/50Hz



<http://www.nts-solution.com>

All features & specifications are subjected to change without notice.

# NTS

บริษัท เอ็นทีเอส อิเล็กทรอนิกส์ โซลูชั่น จำกัด  
NTS Electronic Solution Co., Ltd.

1439-1441 ถนนเจริญนคร แขวงบางลำภูล่าง เขตคลองสาน กรุงเทพฯ 10600

โทรศัพท์: 0-2438-7023-4, 0-2437-7639 โทรสาร: 0-2437-1897

<http://www.nts-solution.com> E-mail: [nts@nts-solution.com](mailto:nts@nts-solution.com)

1439-1441 Charoennakorn Rd. Banglumpoolang Klongsan Bangkok 10600, Thailand

Tel: (+66-2) 438-7023-4, (+66-2) 437-7639 Fax: (+66-2) 437-1897